

► ECC-E | ELECTRICAL

ECC-E | AMP Draw, Circuits & Breaker Size Table

* With optional branch fusing for Single Point Power (SPP)

^ SPP by default

‡ High amp draws may be prohibitive. Reduced and custom kW available. Contact Factory.

+ With internally mounted transformer

++ With motor transformer mounted in remote control panel

AMP DRAW (Breaker Size)

MODEL	208 / 1 / 60		240 / 1 / 60	208 / 3 / 60				240 / 3 / 60			480 / 3 / 60			575 / 3 / 60			
	Separate Supply Circuits		Circuit 1	Separate Supply Circuits				Separate Supply Circuits			Separate Supply Circuits			Separate Supply Circuits			
	1	2		SPP*	1	2	3	SPP*	1	2	SPP*	1	2	SPP*	1	2	SSP*
ECC-1-36E												15.2 (20) ++			12.6 (20) ++		
ECC-1-48E	30.1 (40)	24.0 (35)	54.2 (70)	47.2 (60)	33.8 (45)	-	-	^	29.6 (40)	-	^	15.2 (20) +	-	^	12.6 (20) +	-	^
ECC-1-60E																	
ECC-2-72E												30.3 (40) ++			25.3 (35) ++		
ECC-2-84E	‡	-	‡	‡	40.0 (50)	27.8 (35)	-	67.7 (90)	35.1 (45)	24.1 (35)	59.1 (80)		-	^		-	^
ECC-2-96E												30.3 (40) +			25.3 (35) +		
ECC-2-108E																	
ECC-3-108E												46.5 (60) ++			38.8 (50) ++		
ECC-3-120E	‡	-	‡	‡	46.1 (60)	27.8 (40)	27.8 (40)	‡	47.1 (60)	41.6 (60)	88.7 (125)		-	^		-	^
ECC-3-132E												46.5 (60) +			38.8 (50) +		
ECC-4-144E	‡	-	‡	‡	‡	-	-	‡	‡	-	‡	36.6 (50) ++	24.1 (35)	51 (70)	30.5 (40) ++	20.1 (30) ++	50.6 (70) ++