

## ► ECE-E | ELECTRICAL

### ECE-E | AMP Draw, Circuits & Breaker Size Table

\* With optional branch fusing for Single Point Power (SPP)

^ SPP by default

‡ High amp draws may be prohibitive. Reduced and custom kW available. Contact Factory.

+ With internally mounted transformer

++ With motor transformer mounted in remote control panel

#### AMP DRAW (Breaker Size)

MODEL	208 / 1 / 60		240 / 1 / 60	208 / 3 / 60				240 / 3 / 60			480 / 3 / 60			575 / 3 / 60			
	Separate Supply Circuits		Circuit 1	Separate Supply Circuits				Separate Supply Circuits			Separate Supply Circuits			Separate Supply Circuits			
	1	2		SPP*	1	2	3	SPP*	1	2	SPP*	1	2	SPP*	1	2	SPP*
ECE-1-36E												15.2 (20) ++			12.6 (20) ++		
ECE-1-42E	30.1 (40)	24.0 (35)	54.2 (70)	47.2 (60)	33.8 (45)	-	-	^	29.6 (40)	-	^		-	^		-	^
ECE-1-48E												15.2 (20) +			12.6 (20) +		
ECE-1-60E																	
ECE-2-60E	‡	-	‡	‡	41.6 (60)	12.2 (20)	-	53.8 (70)	47.1 (60)	-	^	n/a	-	-	n/a	-	-
ECE-2-72E												30.3 (40) ++			25.3 (35) ++		
ECE-2-84E	‡	-	‡	‡	40.0 (50)	27.8 (35)	-	67.7 (90)	35.1 (45)	24.1 (35)	59.1 (80)	30.3 (40) +	-	^	25.3 (35) +	-	^
ECE-2-96E																	
ECE-3-108E												46.5 (60) ++			38.8 (50) ++		
ECE-3-120E	‡	-	‡	‡	46.1 (60)	27.8 (40)	27.8 (40)	‡	47.1 (60)	41.6 (60)	88.7 (125)		-	^		-	^
ECE-3-132E												46.5 (60) +			38.8 (50) +		
ECE-4-144E	‡	-	‡	‡	‡	-	-	‡	‡	-	‡	36.6 (50) ++	24.1 (35)	51 (70)	30.5 (40) ++	20.1 (30) ++	50.6 (70) ++