

## ▶ ETA-E | ELECTRICAL

### ETA-E | AMP Draw, Circuits & Breaker Size Table

\* With optional branch fusing for Single Point Power (SPP)

^ SPP by default

‡ High amp draws may be prohibitive. Reduced and custom kW available. Contact Factory.

#### AMP DRAW (Breaker Size)

MODEL	208 / 1 / 60		240 / 1 / 60	208 / 3 / 60			SPP*	240 / 3 / 60			480 / 3 / 60			575 / 3 / 60	
	Separate Supply Circuits			Circuit 1	Separate Supply Circuits			SPP*	Separate Supply Circuits			SPP*			
	1	2	1		2	3	1		2	1	2		Circuit 1		
ETA-1-36E															
ETA-1-42E	27.6	24.0	51.6	45.3	31.4	-	-	^	27.7	-	^	14.0	-	^	11.5
ETA-1-48E	(35)	(35)	(70)	(60)	(40)	-	-		(35)	-		(20)	-		(15)
ETA-1-60E															
ETA-2-72E															
ETA-2-84E	‡	-	‡	‡	35.0	27.8	-	62.7	31.3	24.1	55.4	28.1	-	^	23.1
ETA-2-96E					(45)	(35)	-	(80)	(40)	(35)	(70)	(40)	-		(30)
ETA-3-108E															
ETA-3-120E	‡	-	‡	‡	38.6	27.8	27.8	94.0	46.9	36.1	83.0	42.1	-	^	34.6
ETA-3-132E					(50)	(35)	(35)	(125)	(60)	(50)	(110)	(60)	-		(45)
ETA-4-144E															
ETA-4-156E	‡	-	‡	‡	‡	-	-	‡	‡	-	‡	32.1	24.1	56.2	46.2
ETA-4-168E					(45)	(35)	(80)	(60)							(60)



Model ETA | Top Mount (Threaded Rods)