

▶ ETA-E | ELECTRICAL

ETA-E | AMP Draw, Circuits & Breaker Size Table

* With optional branch fusing for Single Point Power (SPP)

^ SPP by default

‡ High amp draws may be prohibitive. Reduced and custom kW available. Contact Factory.

AMP DRAW (Breaker Size)

MODEL	208 / 1 / 60		240 / 1 / 60	208 / 3 / 60				240 / 3 / 60			480 / 3 / 60			575 / 3 / 60	
	Separate Supply Circuits			SPP*	Circuit 1	Separate Supply Circuits			SPP*	SPP*	Separate Supply Circuits		SPP*		
	1	2	1			2	3	1			2	1		2	Circuit 1
ETA-1-36E															
ETA-1-42E	27.6 (35)	24.0 (35)	51.6 (70)	45.3 (60)	31.4 (40)	-	-	^	27.7 (35)	-	^	14.0 (20)	-	^	11.5 (15)
ETA-1-48E															
ETA-1-60E															
ETA-2-72E															
ETA-2-84E	‡	-	‡	‡	35.0 (45)	27.8 (35)	-	62.7 (80)	31.3 (40)	24.1 (35)	55.4 (70)	28.1 (40)	-	^	23.1 (30)
ETA-2-96E															
ETA-3-108E															
ETA-3-120E	‡	-	‡	‡	38.6 (50)	27.8 (35)	27.8 (35)	94.0 (125)	46.9 (60)	36.1 (50)	83.0 (110)	42.1 (60)	-	^	34.6 (45)
ETA-3-132E															
ETA-4-144E															
ETA-4-156E	‡	-	‡	‡	‡	-	-	‡	‡	-	‡	32.1 (45)	24.1 (35)	56.2 (80)	46.2 (60)
ETA-4-168E															



Model ETA | Top Mount (Threaded Rods)