

▶ ETD & ETD-E | ELECTRICAL

ETD-E | AMP Draw, Circuits & Breaker Size Table

* With optional branch fusing for Single Point Power (SPP)

^ SPP by default

‡ High amp draws may be prohibitive. Reduced and custom kW available. Contact Factory.

AMP DRAW (Breaker Size)

MODEL	208 / 1 / 60		240 / 1 / 60	208 / 3 / 60				240 / 3 / 60			480 / 3 / 60			575 / 3 / 60	
	Separate Supply Circuits		Circuit 1	Separate Supply Circuits			SPP*	Separate Supply Circuits		SPP*	Separate Supply Circuits		SPP*	Circuit 1	
	1	2		1	2	3		1	2		1	2			
ETD-1-36E															
ETD-1-42E	27.6 (35)	24.0 (35)	51.6 (70)	45.3 (60)	31.4 (40)	-	-	^	27.7 (35)	-	^	14.0 (20)	-	^	11.5 (15)
ETD-1-48E															
ETD-1-60E															
ETD-2-60E	‡	-	‡	‡	41.6 (60)	7.2 (15)	-	48.8 (70)	43.3 (60)	-	^	22 (30)	-	^	18.1 (25)
ETD-2-72E															
ETD-2-84E	‡	-	‡	‡	35.0 (45)	27.8 (35)	-	62.7 (80)	31.3 (40)	24.1 (35)	55.4 (70)	28.1 (40)	-	^	23.1 (30)
ETD-2-96E															
ETD-3-108E															
ETD-3-120E	‡	-	‡	‡	38.6 (50)	27.8 (35)	27.8 (35)	94.0 (125)	46.9 (60)	36.1 (50)	83.0 (110)	42.1 (60)	-	^	34.6 (45)
ETD-3-132E															
ETD-4-144E	‡	-	‡	‡	‡	-	-	‡	‡	-	‡	32.1 (45)	24.1 (35)	56.2 (80)	46.2 (60)



Model ETD | Top Mount, Brackets