

## ▶ CLD-E | ELECTRICAL

### CLD-E | AMP Draw, Circuits & Breaker Size Table

\* With optional branch fusing for Single Point Power (SPP)

^ SPP by default

‡ High amp draws may be prohibitive. Reduced and custom kW available. Contact Factory.

MODEL	AMP DRAW (Breaker Size)													
	208 / 1 / 60			240 / 1 / 60	208 / 3 / 60			240 / 3 / 60			480 / 3 / 60			575 / 3 / 60
	Separate Supply Circuits			Circuit 1	Separate Supply Circuits			Separate Supply Circuits			Separate Supply Circuits			Circuit 1
	1	2	SPP*		1	2	SPP*	1	2	SPP*	1	2	SPP*	
CLD-1-36E														
CLD-1-48E	25.4 (35)	24.0 (35)	49.4 (70)	43.1 (60)	29.2 (40)	-	^	25.5 (35)	-	^	12.7 (20)	-	^	10.6 (15)
CLD-1-60E														
CLD-2-72E														
CLD-2-84E	‡	-	‡	‡	30.6 (40)	27.8 (35)	58.4 (80)	26.9 (35)	24.1 (35)	51.0 (70)	25.6 (35)	-	^	21.3 (30)
CLD-2-96E														
CLD-3-108E														
CLD-3-120E	‡	-	‡	‡	45.8 (60)	41.6 (60)	87.4 (110)	40.3 (60)	36.1 (50)	76.4 (100)	38.2 (50)	-	^	31.9 (40)
CLD-3-132E														
CLD-4-144E	‡	-	‡	‡	‡	-	‡	‡	-	‡	26.9 (35)	24.1 (35)	51 (70)	42.8 (60)



Model CLD | Above Ceiling



Model CLD | Above Ceiling