

## ▶ EVE-E | ELECTRICAL

### EVE-E | AMP Draw, Circuits & Breaker Size Table

\* With optional branch fusing for Single Point Power (SPP) - REQUIRES A REMOTE ENCLOSURE

^ SPP By Default

‡ High amp draws may be prohibitive. Reduced and custom kW available. Contact factory.

MODEL	AMP DRAW (Breaker Size)									
	208 / 1 / 60	240 / 1 / 60	208 / 3 / 60			240 / 3 / 60			480 / 3 / 60	575 / 3 / 60
	Circuit 1	Circuit 1	Separate Supply Circuits		SPP*	Separate Supply Circuits		SPP*	Circuit 1	Circuit 1
		1	2		1	2				
EVE-1-36E	40.5 (60)	35.3 (45)	24.2 (35)	-	^	21.2 (30)	-	^	10.7 (15)	8.9 (15)
EVE-1-42E										
EVE-1-48E	‡	‡	46.4 (60)	-	^	40.5 (60)	-	^	20.3 (30)	17.0 (25)
EVE-1-60E										
EVE-2-72E	‡	‡	47.3 (60)	-	^	42.5 (60)	-	^	21.4 (30)	17.9 (25)
EVE-2-84E	‡	‡	26.2 (35)	44.4 (60)	70.6 (90)	23.2 (30)	38.5 (50)	61.7 (80)	31.1 (40)	25.9 (35)
EVE-2-96E										
EVE-2-108E	‡	‡	47.3 (60)	43.3 (60)	90.6 (125)	42.5 (60)	38.5 (50)	81.0 (110)	40.7 (60)	33.9 (45)
EVE-2-120E										



Elite Vestibule Exception Air Curtain | Entry